

Product Code . JL-EE-3621

Auditory Trainers



Description

Auditory Trainers

Amplifier	IC-based output stage coupled with 2 transistor low-noise pre-amp-stage.
Freq. Range	150 Hertz to 8 Khz.
Gain Control	Continuously variable dB Attenuator Max. Volume 130 dB SPL.
Tone Control	2 Tone per channel: Hi-Low (Fixed)
Indicators	Separate indicators(VU Meters)
Switches	For 'Mike' and phono(induction loop system). For battery check.
Microphones	Electret-built in and external
Headphones	Dynamic, low impedance, Adjustable head-band and circumaural ear cushion.
Supply Voltage	6V; 1.5x4 R20(large size) cells if on battery. 230V; 50Hz. A.C. mains with built in power supply.
Current Drain	20 mA, Quiescent.
Max. Power	700 mW, per channel
